

LamaPLC: HDC Texas Instruments Temperature/humidity sensors with I²C communication

The Texas Instruments HDC1080 is a low-power, high-accuracy, factory-calibrated digital humidity and temperature sensor that communicates via an I²C interface.



Key Features

- **High Accuracy:** Provides a typical relative humidity accuracy of $\pm 2\%$ and a typical temperature accuracy of $\pm 0.2^\circ\text{C}$.
- **Low Power Consumption:** Features an ultra-low 100 nA sleep mode current, making it ideal for battery-powered or IoT applications.
- **Integrated Sensing:** Measures both relative humidity and temperature with an integrated sensor element, reducing complexity and footprint.
- **Wide Operating Range & Voltage:**
 - **Supply Voltage:** Operates over a wide range from 2.7 V to 5.5 V.
 - **Temperature Range:** Functional from -40°C to $+125^\circ\text{C}$.
 - **Humidity Range:** Measures 0% to 100% relative humidity.
- **Factory Calibrated:** The sensors are factory-calibrated, ensuring reliable, accurate measurements without requiring user calibration.
- **Digital Interface:** Uses the I²C protocol for easy integration with microcontrollers such as Arduino or ESP32.
- **High Resolution:** Offers 14-bit measurement resolution for precise data acquisition.
- **Stability:** Exhibits excellent stability, particularly in high-humidity environments, with less than 0.5% per year typical drift.
- **On-chip Heater:** Includes a built-in heater that can be used to burn off condensation, enhancing reliability in challenging environmental conditions.

Similar sensors

The **SHT21**, **HTU21**, **Si7021**, **GY-21**, **GY-213V**, and **HDC1080** are very similar digital humidity and temperature sensor chips from different manufacturers (Sensirion, Measurement Specialties, and Silicon Labs, respectively), while the GY-21 is a generic breakout board that uses one of these chips. They are largely interchangeable in hardware and software for most general-purpose applications.



If you'd like to support the development of the site with the price of a coffee — or a few — [please do so here](#).

Here's a handy tip: you can quickly save this page as a PDF by clicking "export to PDF" in the menu on the right side of the screen.

HDC1080 Modul

The **HDC1080 module** (often seen as the **GY-213V-HDC1080** or **CJMCU-1080**) is a breakout board that integrates the Texas Instruments HDC1080 low-power, high-accuracy digital humidity and temperature sensor. It simplifies interfacing with microcontrollers via the I²C bus.



- **Integrated Sensing:** The module measures both relative humidity (0-100%) and temperature (-40°C to +125°C) on a single chip.
- **High Accuracy:** It delivers high-precision measurements with a typical accuracy of $\pm 2\%$ RH and $\pm 0.2^\circ\text{C}$.
- **Wide Operating Voltage:** The board typically supports a 2.7V to 5.5V DC supply range, making it compatible with both 3.3V and 5V systems such as Arduino and Raspberry Pi.
- **Ultra-Low Power:** It features a very low 100 nA sleep mode current, suitable for battery-operated devices.
- **I²C Interface:** Communication is handled via the standard I²C (IIC) protocol, using only SDA and SCL, simplifying wiring to a microcontroller.

Arduino & HDC1080 Modul

- SCL: A5
- GND: GND
- SDA: A4
- Vdd: 5V

Arduino code

To interface the HDC1080 module with an Arduino, the most popular and feature-rich option is the **ClosedCube HDC1080** library.

This sketch initializes the sensor and prints temperature and humidity readings to the Serial Monitor every 3 seconds.

```
#include <Wire.h>
#include "ClosedCube_HDC1080.h"

ClosedCube_HDC1080 hdc1080;

void setup() {
  Serial.begin(9600);

  // Standard I2C address for HDC1080 is 0x40
  hdc1080.begin(0x40);

  Serial.print("Manufacturer ID: 0x");
  Serial.println(hdc1080.readManufacturerId(), HEX); // Should be 0x5449
}
```

```

void loop() {
  // Read temperature and humidity
  float temp = hdc1080.readTemperature();
  float humidity = hdc1080.readHumidity();

  Serial.print("T=");
  Serial.print(temp);
  Serial.print("C, RH=");
  Serial.print(humidity);
  Serial.println("%");

  delay(3000); // Wait for 3 seconds
}

```

I²C topics on lamaPLC

Page	Date	Tags
• lamaPLC Communication: 1-Wire	2026/04/23 21:51	1-wire, communication, bus, microlan, i2c, uart, usart, ds18b20
• lamaPLC Communication: I²C	2025/09/23 21:25	i2c, i c, smbus, philips, bus, communication, arduino
• lamaPLC project: Sension SCD CO² measurement module	2026/04/15 19:34	scd30, scd40, scd41, iaq, ndir, sensor, i2c, arduino code
• LamaPLC: AHT10 Modul	2026/03/22 03:14	communication, i2c, temperature, humidity, sensor, aht, aht 10, modul
• LamaPLC: AHT20 / BMP280 Modul	2026/04/23 21:52	bmp280, aht20, adafruit, temperature, humidity, pressure, sensor, arduino, code, i2c
• LamaPLC: APDS - Avago ALS and proximity detection sensors with I²C communication	2026/04/23 21:52	avago, apds-9900, apds-9930, apds-9960, als, proximity, detection, gesture recognition, gesture, i2c, communication, sensor, arduino, code
• lamaPLC: Arduino Modul: BME680	2026/05/12 18:40	code, c, 2026, arduino, bme680, sensor, i2c, comunication
• lamaPLC: AS5600 Magnetic Induction Angle Measurement Sensor Module	2026/05/13 00:06	communication, i2c, as5600, as-5600, magnetic, induction, angle, sensor
• lamaPLC: Bi-Directional Logic Level Converter 3.3V ↔ 5V	2026/04/12 00:34	bi-directional, logic level converter, i2c, uart, spi
• LamaPLC: BMP/BME Bosch Temperature/Humidity/Pressure sensors with I²C communication	2026/04/23 21:52	bme280, bme680, bme688, bmp180, bmp280, hw-611, hw611, bosch, temperature, humidity, pressure, sensor, arduino, i2c, communication, ai, cjmcu, volatile organic compounds, vocs, volatile sulfur compounds, vscs, iaq
• LamaPLC: CJMCU-219/INA-219 breakout board/IC with I²C communication	2026/04/23 21:52	cjmcu-219, ina-219, ina219, breakout board, i2c, communication, sensor, voltage, current, arduino, code, cjmcu

- [LamaPLC: CJMCU-3216 / AP-3216 integrated digital ambient light and proximity sensor module/IC with I²C communication](#)

2026/04/23 21:52

[cjmcu-3216](#), [cjmcu](#), [ap-3216](#), [ap3216](#), [ambient light](#), [proximity](#), [sensor](#), [arduino](#), [code](#), [i2c](#), [communication](#)
- [lamaPLC: CJMCU-811 CCS811 Gas Sensor \(VOCs TVOC CO2\)](#)

2026/04/23 21:52

[cjmcu-811](#), [ccs811](#), [gas](#), [sensor](#), [vocs](#), [tvoc](#), [eco2](#), [co2](#), [arduino](#), [air quality](#) [metal oxide](#), [mox](#), [i2c](#), [micropython](#), [rp2040-eth](#)
- [LamaPLC: D6T Omron Non-Contact Thermal Sensors with I²C communication](#)

2026/04/23 21:52

[d6t](#), [d6t-32l](#), [d6t-44l](#), [d6t-8l](#), [d6t-1a](#), [omron](#), [non-contact](#), [thermal](#), [sensor](#), [i2c](#), [arduino](#), [code](#)
- [LamaPLC: DPS Infineon Temperature/Pressure sensors with I2C communication](#)

2026/04/23 21:52

[dps310](#), [infineon](#), [temperature](#), [pressure](#), [sensor](#), [arduino](#), [i2c](#), [communication](#), [code](#)
- [lamaPLC: Energy, power, current, and voltage](#)

2025/05/31 23:32

[i2c](#), [i c](#), [communication](#), [arduino](#), [energy](#), [power](#), [current](#), [sensor](#), [ina226](#)
- [LamaPLC: ENS ScioSense Multi-gas sensors with I²C communication](#)

2026/04/23 21:52

[ens160](#), [sciosense](#), [gas-quality](#), [i2c](#), [communication](#), [sensor](#), [arduino](#), [code](#), [eco2](#), [tvoc](#), [aqi](#), [indoor air quality](#), [iaq](#), [co2](#), [voc](#)
- [lamaPLC: ESP32 / ESP8266](#)

2025/11/22 00:07

[esp8266](#), [esp32](#), [esp32-c2](#), [esp32-c3](#), [esp32-c5](#), [esp32-c6](#), [esp32-c61](#), [esp32-h2](#), [esp32-s2](#), [esp32-s3](#), [esp32-p4](#), [espressif systems](#), [communication](#), [ethernet](#), [ip](#), [wi-fi](#), [thread](#), [zigbee](#), [matter](#), [homekit](#), [bluetooth](#), [mqtt](#), [adc](#), [spi](#), [uart](#), [i2c](#), [i2s](#), [rmt](#), [pwm](#), [usb](#), [usb otg](#), [twai](#)
- [LamaPLC: Gas sensors](#)

2023/07/01 17:29

[gas](#), [sensor](#), [i2c](#), [onewire](#), [communication](#), [mq-3](#), [mq-4](#), [mq-5](#), [mq-6](#), [mq-7](#), [mq-8](#), [mq-9](#), [mq-135](#), [gm-102b](#), [gm-302b](#), [gm-502b](#), [gm-702b](#), [alcohol](#), [ch4](#), [natural gas](#), [smoke](#), [lng](#), [co](#), [co2](#), [lpg](#), [h2](#), [iso-butane](#), [nox](#), [nh3](#), [benzene](#), [town gas](#), [formaldehyde](#), [propane](#), [humidity](#), [temperature](#), [voc](#), [grv gas sens v2](#)
- [lamaPLC: GY-511 6DOF sensor module](#)

2026/04/23 21:52

[stmicroelectronics](#), [lsm303dlhc](#), [i2c](#), [lsm303](#), [sensor](#), [gy-511](#), [6dof](#), [pololu](#), [module](#), [arduino](#)
- [LamaPLC: GY-9250 MPU-9250/6500 9-axis Attitude Sensor Board](#)

2026/04/23 21:52

[ak8963](#), [gy-9250](#), [mpu-9250](#), [9-axis](#), [motion detection](#), [magnetometer](#), [communication](#), [i c](#), [i2c](#), [spi](#)
- [LamaPLC: HDC Texas Instruments Temperature/humidity sensors with I²C communication](#)

2026/04/23 21:52

[sht21](#), [htu21](#), [si7021](#), [gy-21](#), [gy-213v](#), [hdc1080](#), [gy-213v-hdc1080](#), [cjmcu](#), [cjmcu-1080](#), [texas instruments](#), [temperature](#), [humidity](#), [sensor](#), [i2c](#), [communication](#), [arduino](#), [code](#)
- [lamaPLC: HT16K33 display controller](#)

2026/04/23 21:51

[i2c](#), [7-segment display](#), [display](#), [ht16k33](#), [arduino](#)

<ul style="list-style-type: none"> • LamaPLC: HTU TE Connectivity temperature/humidity sensors with I²C communication 	2026/04/23 21:52	htu, htu31d, htu21d, htu20d, sht20, htu20, sht21, htu21, si7021, gy-21, gy-213v, hdc1080, si702, gy-20, sht31, htu31, si7031, gy-31, te connectivity, temperature, humidity, i2c, communication, sensor, arduino, code
<ul style="list-style-type: none"> • lamaPLC: INA modules with Arduino libraries 	2026/04/23 21:52	energy, power, current, monitor, sensor, ina219, gy-219, ina226, gy-216, ina228, gy-228, ina237, ina238, ina260, ina3221, ina
<ul style="list-style-type: none"> • lamaPLC: INA226 - current/voltage/power monitor with I²C communication 	2026/04/23 21:52	i2c, i c, communication, arduino, energy, power, current, monitor, sensor, ina226, ina219, ina
<ul style="list-style-type: none"> • lamaPLC: LCD 1602/2004 with I²C communication 	2026/02/14 18:27	communication, i2c, display, lcd, 1602, 2004, hd44780, pcf8574, pcf8574t, pcf8574at, arduino
<ul style="list-style-type: none"> • LamaPLC: MAX30100/MAX30102 Heart Rate Click Sensor Module 	2026/04/23 21:52	max30102, max30100, heart rate click, sensor, communication, i2c, arduino, code
<ul style="list-style-type: none"> • lamaPLC: MCP23017 / MCP23S17 16-Bit I/O Expander with Serial Interface I²C / SPI 	2026/04/23 21:52	communication, i2c, mcp23017, mcp23s17, spi, i o expander, serial, cjmcu-2317, cjmcu
<ul style="list-style-type: none"> • lamaPLC: MLX90614 (GY-906) infrared non-contact thermometer 	2026/05/08 00:03	communication, i2c, temperature, mlx90614, gy-906, modul, infrared, non-contact thermometer, dsp, pwm, smbus, hailege
<ul style="list-style-type: none"> • lamaPLC: PCF857x I/O Expander chip/modul with I²C communication 	2026/05/15 01:03	communication, i2c, pcf857x, pcf8574, pcf8574a, pcf8575, i o expander, i o extension, nxp, texas instruments
<ul style="list-style-type: none"> • LamaPLC: Pixart PAJ7620U2 Gesture recognition sensors/module with I²C communication 	2026/04/23 21:52	paj7620u2, gy-paj7620, pixart, gesture recognition, i2c, communication, sensor, arduino, code
<ul style="list-style-type: none"> • lamaPLC: RP2040_ETH_Modul: I²C scanner 	2026/05/12 16:20	code, micropython, 2026, rp2040 eth, i2c, comunication
<ul style="list-style-type: none"> • lamaPLC: RP2040_ETH_Modul: MLX90614 simple 	2026/05/12 17:06	code, micropython, 2026, rp2040 eth, i2c, communication, mlx90614
<ul style="list-style-type: none"> • lamaPLC: RP2040_ETH_Modul: Read BME 680/688 sensor data 	2026/05/12 21:06	code, micropython, 2026, rp2040 eth, bme680, i2c, sensor, communication
<ul style="list-style-type: none"> • lamaPLC: RP2040_ETH_Modul: Read BME 680/688 sensor data and store in Modbus input registers 	2026/05/12 18:58	code, micropython, 2026, rp2040 eth, bme680, i2c, sensor, communication
<ul style="list-style-type: none"> • LamaPLC: SC16IS750 / SC16IS752: One or two serial (UART) ports from microcontroller via I²C or SPI communication 	2026/04/23 21:52	cjmcu-750, cjmcu-752, cjmcu, nxp, sc16is750, sc16is752, uart, serial, i2c, spi, modul, converter, arduino, code
<ul style="list-style-type: none"> • LamaPLC: SGP Sensirion TVOC/VOC sensors with I²C communication 	2026/04/15 19:41	sgp30, sgp40, sgp41, sensirion, gas-sensor, i2c, communication, sensor, arduino, code, eco2, voc, tvoc, indoor air quality, iaq, nox, hydrogen

- [LamaPLC: SHT Sensirion Temperature/humidity sensor with I²C communication](#)

 2026/04/23
21:52

[sht20, sht21, sht25, sht30, sht31, sht35, sht40, gy21, temperature, humidity, i2c, communication, sensor, arduino, code](#)

- [lamaPLC: Signal level converters](#)

 2026/02/14
23:47

[pca9306, i2c, voltage, level, converter](#)

- [lamaPLC: st756x display drivers](#)

 2026/05/20
16:17

[display, driver, i2c, spi, lcd, cog, oled, st7565, st7567, gm12864, gm12864-59n, gm12864-03a, gm12864-01a, gme12864-41](#)

- [lamaPLC: TCA9548A \(HW617\); Low-Voltage 8-Channel I²C Switch Module](#)

 2026/02/14
23:51

[tca9548a, hw617, i2c, switch, communication, expansion board, arduino](#)

- [lamaPLC: TM1637 7-segment display](#)

 2026/02/14
18:26

[i2c, 7-segment display, display, tm1637, arduino](#)

- [LamaPLC: TOFnnnC STMicroelectronics Time-of-Flight \(ToF\) sensors with I²C communication](#)

 2026/04/23
21:52

[tof050c, vl6180, tof200c, vl5310x, tof400c, vl5311x, stmicroelectronics, time-of-flight, tof, i2c, communication, sensor, arduino, code](#)

- [LamaPLC: VL53Lnn STMicroelectronics time-of-flight \(ToF\) laser-ranging sensors with I²C communication](#)

 2026/04/23
21:52

[vl5310x, vl5311x, vl5310 1xv2, gy-530, time-of-flight, tof, laser-ranging, i2c, communication, sensor, arduino, code](#)

- [LamaPLC: VL6180X STMicroelectronics Time-of-Flight \(ToF\) sensor with I²C communication](#)

 2026/04/23
21:52

[vl6180x, stmicroelectronics, time-of-flight, tof, i2c, communication, sensor, arduino, code](#)

- [lamaPLC: XGZP68xx: Silicon Pressure Sensors/Module](#)

 2026/05/15
15:17

[communication, i2c, sensor, modul, pressure, cfsensor, xgzp68xx, xgzp6810d, xgzp6857d, xgzp6859d, xgzp6887d, xgzp6897d, xgzp6899a, piezoresistive, capacitive](#)

- [Magnetic angle sensors](#)

 2026/04/23
21:52

[magnetic angle sensor, magnetic flux, sensor, spi, i2c, pwm, communication, modul, as5047p, as5600, mt6701, mt6816, mt6835, tle5012b, amr, gmr, tmr, anisotropic magnetoresistive](#)

- [SSH1106/SSD1306 OLED Display with I²C communication](#)

 2026/02/14
18:27

[i2c, oled, display, ssd1306, sh1106, ssh1106, arduino, cmos](#)

[SHT21, HTU21, Si7021, GY-21, GY-213V, HDC1080, GY-213V-HDC1080, CJMCU, CJMCU-1080, Texas Instruments, temperature, humidity, sensor, i2c, communication, arduino, code](#)

This page has been accessed for: Today: 3, Until now: 174

From:
<https://lamaplc.de/> - **lamaPLC**

Permanent link:
<https://lamaplc.de/doku.php?id=sensor:hdc>

Last update: **2026/04/21 20:47**



