

LamaPLC: RGB / RGBW addressable LEDs

The **WS28xx** (*WorldSemi*) series consists of addressable RGB LEDs that integrate a driver IC and LED chips into a single package or circuit. These LEDs allow for individual control of color and brightness through a single-wire digital signal, making them popular for custom lighting projects.



The SK6812 is an individually addressable LED driver IC often considered the direct successor or “*upgraded version*” of the WS2812B. While it shares the same single-wire control protocol, it introduces a dedicated fourth channel for true white light (RGBW) and operates at a higher PWM frequency for smoother dimming.


Code Compatibility

If you swap a WS2812B (RGB) strip for an SK6812 (RGBW) strip, you must update your code. The controller needs to send 32 bits instead of 24. If you don't, the colors will “shift” down the line, appearing as static or incorrect.

Popular WS28xx Models

The series uses a common communication protocol, but models vary in voltage, control accuracy, and reliability.

- **WorldSemi WS2812B (Standard 5V):** The most common model, with the IC embedded directly within the 5050 LED package. It runs on 5V DC, enabling high pixel density since each LED is individually addressable. However, it lacks a backup data line; if an LED fails, the signal can't pass through to the rest of the strip.
- **WorldSemi WS2811 (External IC 12V/24V):** This model employs an external driver chip, usually mounted on the PCB rather than inside the LED. In strips, it typically controls groups of three LEDs as a single pixel, reducing detail in complex animations but offering a cost-effective solution for large displays.



- **WorldSemi WS2813 (Reliable 5V):** An improved version of the WS2812B, featuring a dual-signal data line. Its “breakpoint resume” function ensures the strip continues working if one LED fails (except when two consecutive LEDs fail). It also has a higher PWM frequency (2kHz versus 400Hz) for smoother dimming.
- **WorldSemi WS2815 (Reliable 12V):** Similar to the WS2813 but operates on 12V DC. This higher voltage greatly minimizes “*voltage drop*,” allowing longer runs (up to 5 meters) without requiring power injection at multiple points. It also includes a backup data line, like the WS2813.


Technical Comparison

Feature	WS2811	WS2812B	WS2813	WS2815	SK6812
Voltage	12V / 24V	5V	5V	12V	5V (mostly)
Color Channels	3 (RGB)	3 (RGB)	3 (RGB)	3 (RGB)	4 (RGB + White)
Data Length	24-bit per pixel	24-bit per pixel	24-bit per pixel	24-bit per pixel	32-bit per pixel
PWM Frequency	~400 Hz	~400 Hz	~2.0 kHz	~2.0 kHz	~1.2 kHz
Addressability	3-LED segments	Individual	Individual	Individual	Individual
Backup Data	No	No	Yes (Dual signal)	Yes (Dual signal)	No
White Quality	Mixed (Blue-ish)	Mixed (Blue-ish)	Mixed (Blue-ish)	Mixed (Blue-ish)	Pure (Dedicated chip)
IC Location	External	Built-in	Built-in	Built-in	Built-in

Selection Guide Choosing the right model depends on the scale and complexity of your project:



- For high-density, short runs: Use **WS2812B** for its low cost and individual control.
- For long-distance installations: Use **WS2815** to minimize voltage drop and increase reliability with its backup data line.
- For large-scale budget lighting: Use **WS2811 (12V)** when individual control of every LED is not required.
- For critical failure prevention: Use **WS2813 (5V)** or **WS2815 (12V)** so a single dead LED doesn't break the entire animation.
- The **WS2813** and **WS2815** are superior for permanent installations because of their dual data lines. If one LED dies, the signal jumps to the next.
- **SK6812** wins if you need high-quality white light. Because it has a dedicated white phosphor chip, you can achieve "Warm White" or "Natural White" that looks like a real light bulb.



If you'd like to support the development of the site with the price of a coffee — or a few — [please do so here](#).

Here's a handy tip: you can quickly save this page as a PDF by clicking "export to PDF" in the menu on the right side of the screen.

2026/02/14 23:38

LEDs Addressing

The WS28xx series uses a daisy-chain addressing mechanism where each LED (or group of LEDs) has no fixed hardware address. Instead, they are indexed by their physical position in the chain.

The communication follows a "data-stripping" or "self-addressing" protocol:

- **Data Packet Intake:** The first LED in the series receives a long stream of data from the controller. It "takes" the first 24 bits (8 bits each for Green, Red, and Blue) and applies that color to itself.

- **Signal Forwarding:** After consuming its 24 bits, the first LED reshapes the remaining signal and passes it to the next LED via its Data Out (DOUT) pin.
- **Sequential Processing:** The second LED now treats the next 24 bits as its own, consumes them, and passes the remaining bits down the line. This process repeats until every LED has received its 24-bit color value.
- **Reset Signal:** To finalize the update, the controller holds the data line low (typically for > 50 μ s), which “latches” the colors and prepares the LEDs for the next frame.

Arduino & Addressable LEDs

Example 1: Arduino & WS2812B

To control WS2812B LEDs with an Arduino, the **FastLED** and Adafruit NeoPixel Libraries are the most popular options. Both require you to define the data pin, the number of LEDs, and the color order (usually GRB for WS2812B).

FastLED is highly optimized and offers advanced color control features like HSV (Hue, Saturation, Value).

```
#include <FastLED.h>

#define LED_PIN      6           // Pin connected to Din on the strip
#define NUM_LEDS    10          // Number of LEDs in your strip
#define BRIGHTNESS  50          // Set brightness (0-255)
#define LED_TYPE     WS2812B    // Model type
#define COLOR_ORDER  GRB        // Standard for WS2812B

CRGB leds[NUM_LEDS];           // Initialize the LED array

void setup() {
  // Power-up safety delay
  delay(3000);
  FastLED.addLeds<LED_TYPE, LED_PIN, COLOR_ORDER>(leds, NUM_LEDS);
  FastLED.setBrightness(BRIGHTNESS);
}

void loop() {
  // Simple "Larson Scanner" effect
  for(int i = 0; i < NUM_LEDS; i++) {
    leds[i] = CRGB::Blue;       // Set current LED to Blue
    FastLED.show();             // Update the strip
    delay(50);
    leds[i] = CRGB::Black;     // Turn it off for the next frame
  }
}
```

Important Hardware Considerations

- **Power:** Each LED can draw up to 60mA at full white brightness. For more than 10–15 LEDs, use an external 5V power supply rather than the Arduino's 5V pin to avoid damage.
- **Common Ground:** If using an external power source, you must connect the power supply's ground (GND) to the Arduino's GND pin.
- **Protection:** Place a 330–470 Ω resistor between the Arduino data pin and the strip's DIN to prevent signal spikes.

Example 1: Arduino & SK6812

To control SK6812 RGBW LEDs, you must account for the fourth white channel. If you use standard RGB code, the colors will “drift” because the strip expects 32 bits per pixel instead of 24.

The Adafruit NeoPixel Library is the easiest way to handle the extra white channel on Arduino.

This script cycles through Red, Green, Blue, and then the Dedicated White chip.

```
#include <Adafruit_NeoPixel.h>

#define PIN          6    // Data pin
#define NUMPIXELS    10  // Number of LEDs

// IMPORTANT: Use 'NEO_GRBW' for SK6812 RGBW models
Adafruit_NeoPixel strip(NUMPIXELS, PIN, NEO_GRBW + NEO_KHZ800);

void setup() {
  strip.begin();
  strip.setBrightness(50); // Set brightness (0-255)
  strip.show();           // Initialize all pixels to 'off'
}

void loop() {
  // 1. Pure Red
  colorWipe(strip.Color(255, 0, 0, 0), 50);

  // 2. Pure Green
  colorWipe(strip.Color(0, 255, 0, 0), 50);

  // 3. Pure Blue
  colorWipe(strip.Color(0, 0, 255, 0), 50);

  // 4. Pure White (Using the dedicated 4th channel)
  colorWipe(strip.Color(0, 0, 0, 255), 50);

  // 5. Warm Mix (RGB + White)
  colorWipe(strip.Color(100, 50, 0, 200), 50);
}

// Function to fill dots one after the other with a color
void colorWipe(uint32_t color, int wait) {
```

```

for(int i=0; i<strip.numPixels(); i++) {
  strip.setPixelColor(i, color);
  strip.show();
  delay(wait);
}
}

```

Key Differences in SK6812 Code:

1. The Flag: You must use NEO_GRBW in the setup. If your LEDs are the “Warm White” or “Cool White” specific version, the order might occasionally be NEO_WRGB, but NEO_GRBW is the industry standard for [SK6812 Datasheet](#) specifications.
2. The Color Command: `strip.Color(R, G, B, W)` now accepts a fourth parameter.
 1. `strip.Color(0, 0, 0, 255)` turns on only the white element (most efficient).
 2. `strip.Color(255, 255, 255, 0)` mixes RGB to make white (less accurate, uses more power).

Hardware Tip for SK6812

Since SK6812 strips have four emitters per pixel, they draw more current than WS2812B strips. Ensure your 5V power supply can handle roughly 80 mA per pixel if you plan to run both RGB and white channels at full brightness simultaneously.

Sensor topics on lamaPLC

Page	Date	Tags
• lamaPLC project: Arduino - OLED SH1106 with AHT20/BMP280 Sensor	2026/04/23 21:51	bmp280 , aht20 , temperature , humidity , pressure , sensor , arduino , oled , sh1106 , arduino code
• lamaPLC project: Arduino - Vibration sensors	2026/04/15 17:21	vibration , sensor , piezoelectric , mems , eddy-current , electrodynamic , gxfm0459 , ldtm-028k , arduino , arduino code
• lamaPLC project: Digitales Potentiometer Board Moduls	2026/04/11 18:29	sensor , module , arduino code , renesas , x9c series , x9c102 , x9c103 , x9c104 , x9c503 , xdcp , digitally controlled potentiometer
• lamaPLC project: Sension SCD CO² measurement module	2026/04/15 19:34	scd30 , scd40 , scd41 , iaq , ndir , sensor , i2c , arduino code
• lamaPLC: A0221AU / A02YYUW Waterproof Ultrasonic Distance Sensor with UART communication	2026/04/23 21:52	a0221au , a02yyuw , waterproof , ultrasonic , distance , sensor , uart , ip67 , serial , sen0311 , dfrobot
• LamaPLC: AHT10 Modul	2026/03/22 03:14	communication , i2c , temperature , humidity , sensor , aht , aht 10 , modul
• LamaPLC: AHT20 / BMP280 Modul	2026/04/23 21:52	bmp280 , aht20 , adafruit , temperature , humidity , pressure , sensor , arduino , code , i2c

• LamaPLC: Allegro ACS758 Hall-effect linear current sensors	2026/04/23 21:52	cjmcu , cjmcu-758 , acs758 , acs758lcb-050b , acs758lcb-100b , acs758kcb-150b , acs758ecb-200b , hall-effect , current , sensor , analog , arduino , code
• LamaPLC: APDS - Avago ALS and proximity detection sensors with I²C communication	2026/04/23 21:52	avago , apds-9900 , apds-9930 , apds-9960 , als , proximity , detection , gesture recognition , gesture , i2c , communication , sensor , arduino , code
• lamaPLC: Arduino Modul: BME680	2026/05/12 18:40	code , c , 2026 , arduino , bme680 , sensor , i2c , comunication
• lamaPLC: AS5600 Magnetic Induction Angle Measurement Sensor Module	2026/05/13 00:06	communication , i2c , as5600 , as-5600 , magnetic , induction , angle , sensor
• LamaPLC: BMP/BME Bosch Temperature/Humidity/Pressure sensors with I²C communication	2026/04/23 21:52	bme280 , bme680 , bme688 , bmp180 , bmp280 , hw-611 , hw611 , bosch , temperature , humidity , pressure , sensor , arduino , i2c , communication , ai , cjmcu , volatile organic compounds , vocs , volatile sulfur compounds , vscs , iaq
• LamaPLC: BQ25570 / CJMCU-2557 - Texas Instruments nano-power management IC and module	2026/04/23 21:52	bq25570 , sensor , texas instruments , nano-power management , dc-dc boost charger , mppt , solar , thermoelectric , piezoelectric , energy harvesting , eh
• LamaPLC: CJMCU-219/INA-219 breakout board/IC with I²C communication	2026/04/23 21:52	cjmcu-219 , ina-219 , ina219 , breakout board , i2c , communication , sensor , voltage , current , arduino , code , cjmcu
• LamaPLC: CJMCU-3216 / AP-3216 integrated digital ambient light and proximity sensor module/IC with I²C communication	2026/04/23 21:52	cjmcu-3216 , cjmcu , ap-3216 , ap3216 , ambient light , proximity , sensor , arduino , code , i2c , communication
• LamaPLC: CJMCU-3901/PMW-3901 compact optical flow sensor module/IC by PixArt with SPI communication	2026/04/23 21:52	cjmcu-3901 , cjmcu , pmw3901 , pmw-3901 , optical flow , sensor , pixart , spi , communication , arduino , code , pmw3901mb-txqt
• LamaPLC: CJMCU-6701: Biosensor for measuring Galvanic Skin Response (GSR) with SPI communication	2026/04/23 21:52	cjmcu , cjmcu-6701 , acs758 , acs-758 , galvanic skin response , gsr , electrodermal activity , eda , spi , communication , arduino , code , sensor , healthcare
• LamaPLC: CJMCU-6814 combined gas sensor module for CO, NO₂, NH₃	2026/04/23 21:52	analog , cjmcu , cjmcu-6814 , mics6814 , mics-6814 , sensor , arduino , code , carbon monoxide , co , ammonia , nh₃ , nitrogen dioxide , no₂
• lamaPLC: CJMCU-811 CCS811 Gas Sensor (VOCs TVOC CO₂)	2026/04/23 21:52	cjmcu-811 , ccs811 , gas , sensor , vocs , tvoc , eco2 , co2 , arduino , air quality , metal oxide , mox , i2c , micropython , rp2040-eth
• LamaPLC: CJMCU-8221 Analog Devices Precision instrumentation amplifier module	2026/04/23 21:52	cjmcu-8221 , ad8221ar , analog devices , amplifier , sensor , cjmcu

• LamaPLC: D6T Omron Non-Contact Thermal Sensors with I ² C communication	2026/04/23 21:52	d6t, d6t-32l, d6t-44l, d6t-8l, d6t-1a, omron, non-contact, thermal, sensor, i2c, arduino, code
• LamaPLC: DHT Temperature /Humidity sensors with 1-wire / I ² C communication	2026/04/23 21:52	dht11, dht20, dht22, temperature, humidity, pressure, sensor, 1-wire, arduino, code
• LamaPLC: DPS Infineon Temperature/Pressure sensors with I2C communication	2026/04/23 21:52	dps310, infineon, temperature, pressure, sensor, arduino, i2c, communication, code
• lamaPLC: DS18B20 1-Wire Digital Thermometer	2026/04/23 21:52	ds18b20, sensor, 1-wire, communication, arduino, thermometer, parasitic mode
• lamaPLC: Energy, power, current, and voltage	2025/05/31 23:32	i2c, i c, communication, arduino, energy, power, current, sensor, ina226
• LamaPLC: ENS ScioSense Multi-gas sensors with I ² C communication	2026/04/23 21:52	ens160, sciosense, gas-quality, i2c, communication, sensor, arduino, code, eco2, tvoc, aqi, indoor air quality, iaq, co2, voc
• lamaPLC: ENS160 + AHT21 Air Quality Sensor - CO, ECO, TVOC, Temp & Humidity Module	2026/04/23 21:52	arduino, ens160, aht21, air quality, sensor, co, eco, tvoc, module, aqi
• LamaPLC: Gas sensors	2023/07/01 17:29	gas, sensor, i2c, onewire, communication, mq-3, mq-4, mq-5, mq-6, mq-7, mq-8, mq-9, mq-135, gm-102b, gm-302b, gm-502b, gm-702b, alcohol, ch4, natural gas, smoke, lng, co, co2, lpg, h2, iso-butane, nox, nh3, benzene, town gas, formaldehyde, propane, humidity, temperature, voc, grv gas sens v2
• LamaPLC: GM MEMS Gas-sensors	2026/04/23 21:52	gm-102b, gm-302b, gm-502b, gm-702b, mems, gas-quality, sensor, arduino, code, nitrogen dioxide, no2, volatile organic compounds, voc, carbon monoxide, co, ethyl alcohol, c2h5ch, formaldehyde, ch2o, alcohol, c2h5oh
• lamaPLC: GY-511 6DOF sensor module	2026/04/23 21:52	stmicroelectronics, lsm303dlhc, i2c, lsm303, sensor, gy-511, 6dof, pololu, module, arduino
• LamaPLC: HC-SR04 Ultrasonic Sensor Module	2026/04/23 21:52	hc-sr04, ultrasonic, sensor, arduino, code
• LamaPLC: HDC Texas Instruments Temperature/humidity sensors with I ² C communication	2026/04/23 21:52	sht21, htu21, si7021, gy-21, gy-213v, hdc1080, gy-213v-hdc1080, cjmcu, cjmcu-1080, texas instruments, temperature, humidity, sensor, i2c, communication, arduino, code
• LamaPLC: HTU TE Connectivity temperature/humidity sensors with I ² C communication	2026/04/23 21:52	htu, htu31d, htu21d, htu20d, sht20, htu20, sht21, htu21, si7021, gy-21, gy-213v, hdc1080, si702, gy-20, sht31, htu31, si7031, gy-31, te connectivity, temperature, humidity, i2c, communication, sensor, arduino, code

• LamaPLC: HX711 24-bit analog-to-digital converter (ADC)	2026/04/11 18:28	hx711 , hx-711 , analog-to-digital , adc , converter , load cell , wheatstone bridge , weight , sensor , communication , arduino , code
• lamaPLC: INA modules with Arduino libraries	2026/04/23 21:52	i2c , i c , communication , arduino , energy , power , current , monitor , sensor , ina219 , gy-219 , ina226 , gy-216 , ina228 , gy-228 , ina237 , ina238 , ina260 , ina3221 , ina
• lamaPLC: INA226 - current/voltage/power monitor with I²C communication	2026/04/23 21:52	i2c , i c , communication , arduino , energy , power , current , monitor , sensor , ina226 , ina219 , ina
• lamaPLC: LTC3588 - Nanopower energy harvesting power supply IC	2026/04/23 21:52	communication , arduino , sensor , energy harvesting , eh , energy , ambient power
• LamaPLC: M01 - V0.4 Laser ranging sensor with UART communication	2026/04/23 21:52	distance measurement , laser , distance , sensor , m01
• LamaPLC: MAX30100/MAX30102 Heart Rate Click Sensor Module	2026/04/23 21:52	max30102 , max30100 , heart rate click , sensor , communication , i2c , arduino , code
• lamaPLC: Max31865 RTD to Digital Converter - PT100/PT1000 Platine	2026/04/23 21:52	max31865 , rtd , pt 100 , pt 1000 , temperature , spi , platinum , arduino , code , sensor , adafruit
• LamaPLC: MAX4466/MAX9814: Low-noise Microphone Preamplifiers	2026/04/23 21:52	audio , microphone , analogue audio , max4466 , max9814 , max 4466 , max 9814 , agc , preamplifiers , sensor , arduino , code
• LamaPLC: MH-Z19 series of NDIR CO₂ sensors	2026/04/23 21:52	mh-z19 , mh-z19d , mh-z19c , mh-z19b , mh-z19e , ndir , co₂ , sensor , winsen , uart , pwm , communication , non-dispersive infrared , infrared , ir , temperature , arduino , code , tasmota
• lamaPLC: MPU-6050 (HW-123, GY-521) 6-axis MotionTracking device	2026/04/23 21:52	mpu-6050 , hw-123 , gy-521 , 6-axis motiontracking , dmp , temperature , sensor , mems , arduino code , arduino , accelerometer , gyroscope , tilt
• LamaPLC: MQ Winsen Gas-sensors	2026/04/23 21:52	mq , mq-2 , mq-3 , mq-4 , mq-5 , mq-6 , mq-7 , mq-8 , mq-9 , mq-131 , mq-135 , mq-137 , winsen , gas-sensor , sensor , arduino , code , alcohol , c₂h₅oh , benzine gas , smoke , lpg , propane , c₃h₈ , hydrogen , h₂ , methane , ch₄ , iso-butane , town gas , ammonia , nh₃
• LamaPLC: PIR sensors	2026/04/23 21:52	hc-sr501 , hc-sr505 , am-312 , ekmb ekmc , pir , motion , sensor , arduino , code
• LamaPLC: Pixart PAJ7620U2 Gesture recognition sensors/module with I²C communication	2026/04/23 21:52	paj7620u2 , gy-paj7620 , pixart , gesture recognition , i2c , communication , sensor , arduino , code
• lamaPLC: PT100 / PT1000	2025/09/23 18:59	pt100 , pt1000 , temperature , sensor , platine , rtd
• lamaPLC: PTA8C04 4-channel PT100 Modbus Modul	2026/02/14 18:42	pta8c04 , sensor , modbus , rtu , rs-485 , communication , platine , um72

• LamaPLC: RCWL - Microwave radar sensor	2026/04/23 21:52	rcwl-0516, rcwl, microwave, radar, sensor, arduino, code
• lamaPLC: RD-xx - Ai-Thinker Radar Module with UART communication	2026/04/23 21:52	radar, s3km1110, fmcw, rd-01, rd-03, rd-03d, ai-thinker, k-band, 24 ghz, sensor, distance, micro-movements
• lamaPLC: RP2040_ETH_Modul: Read BME 680/688 sensor data	2026/05/12 21:06	code, micropython, 2026, rp2040 eth, bme680, i2c, sensor, communication
• lamaPLC: RP2040_ETH_Modul: Read BME 680/688 sensor data and store in Modbus input registers	2026/05/12 18:58	code, micropython, 2026, rp2040 eth, bme680, i2c, sensor, communication
• LamaPLC: SGP Sensirion TVOC/VOC sensors with I ² C communication	2026/04/15 19:41	sgp30, sgp40, sgp41, sensirion, gas-sensor, i2c, communication, sensor, arduino, code, eco2, voc, tvoc, indoor air quality, iaq, nox, hydrogen
• LamaPLC: SHT Sensirion Temperature/humidity sensor with I ² C communication	2026/04/23 21:52	sht20, sht21, sht25, sht30, sht31, sht35, sht40, gy21, temperature, humidity, i2c, communication, sensor, arduino, code
• LamaPLC: Texas Instruments ADCs: Delta-sigma multi-channel Analog Converters with SPI communication	2026/04/23 21:52	ads111x, ads12xx, delta-sigma, converter, texas instruments, adc, spi, communication, sensor, arduino, code, ads1110, ads1112, ads1113, ads1114, ads1115, ads1118, ads1119, ads1220, ads1232, ads1234, ads1256, ads1261, ads1263, multi channel
• LamaPLC: TOFnnnC STMicroelectronics Time-of-Flight (ToF) sensors with I ² C communication	2026/04/23 21:52	tof050c, vl6180, tof200c, vl53l0x, tof400c, vl53l1x, stmicroelectronics, time-of-flight, tof, i2c, communication, sensor, arduino, code
• LamaPLC: UICPAL Temp.humi.sensor	2023/06/25 00:43	simatic, s7, modbus, communication, temperature, humidity, sensor
• LamaPLC: VL53Lnn STMicroelectronics time-of-flight (ToF) laser-ranging sensors with I ² C communication	2026/04/23 21:52	vl53l0x, vl53l1x, vl53l0 1xv2, gy-530, time-of-flight, tof, laser-ranging, i2c, communication, sensor, arduino, code
• LamaPLC: VL6180X STMicroelectronics Time-of-Flight (ToF) sensor with I ² C communication	2026/04/23 21:52	vl6180x, stmicroelectronics, time-of-flight, tof, i2c, communication, sensor, arduino, code
• LamaPLC: Waveshare TOF Laser Range Sensor with UART / I ² C communication	2026/04/23 21:52	distance measurement, laser, range, sensor, tof, waveshare
• lamaPLC: XGZP68xx: Silicon Pressure Sensors/Module	2026/05/15 15:17	communication, i2c, sensor, modul, pressure, cfsensor, xgzp68xx, xgzp6810d, xgzp6857d, xgzp6859d, xgzp6887d, xgzp6897d, xgzp6899a, piezoresistive, capacitive
• lamaPLC: YR-3180 - Weight sensor module with UART or Modbus communication	2026/02/15 00:00	communication, modbus, rtu, sensor, weight, yr-3180, hx710b, arduino, ttl, rs-485
• LM393: Dual differential comparator (flame, light, sound sensors)	2026/05/12 22:18	communication, analog, lm393, lm-393, flame, ir, sound, hall, sensor, ky-026, hw-484, ky-037, ky-038, fc-03, hc-89, ky-024, modul

- [Magnetic angle sensors](#) 2026/04/23 21:52 [magnetic angle sensor](#), [magnetic flux sensor](#), [spi](#), [i2c](#), [pwm](#), [communication](#), [modul](#), [as5047p](#), [as5600](#), [mt6701](#), [mt6816](#), [mt6835](#), [tle5012b](#), [amr](#), [gmr](#), [tmr](#), [anisotropic magnetoresistive](#)
- [NT18B07: 7 Kanal RS485 Temperatur Sensor with Modbus RTU](#) 2026/02/14 18:49 [nt18b07](#), [sensor](#), [modbus](#), [rtu](#), [rs-485](#), [communication](#), [platine](#)
- [PT100 / PT1000 sensors](#) 2026/04/23 21:52 [rtd](#), [pt100](#), [pt1000](#), [sensor](#), [temperature](#)
- [Radar Module RD-xx](#) 2026/04/23 21:52 [radar](#), [s3km1110](#), [fmcw](#), [rd-03](#), [k-band](#), [24 ghz](#), [sensor](#), [distance](#), [micro-movements](#)

[addressable LED](#), [LED](#), [WorldSemi](#), [SK6812](#), [WS2811](#), [WS2812B](#), [WS2813](#), [WS2815](#), [NeoPixel](#), [FastLED](#), [aktor](#), [arduino](#), [code](#)

This page has been accessed for: Today: 1, Until now: 148

From:
<http://lamaplc.com/> - **lamaPLC**

Permanent link:
<http://lamaplc.com/doku.php?id=actor:ws28xx>

Last update: **2026/04/21 20:48**

